SPECIFICATION FOR APPROVAL

	APPROVED BY	CUSTOMER
CUSTOMER:		
MODULE FAMILY:_	I.T.E. PC	OWER SUPPLY
PART NO:		REVISION :A
MODEL NO.:	ST241A	SAFETY :UL/c-UL
DESIGN NO. :		DATE: Feb.06.2009

Reviewed by	Approved by
	Reviewed by



Specification Index

Item	Documentation		Page			
1	Sample revisions		03			
2	General specification		04-06			
3	PCB Layout		07			
4	Mechanical Requirements		08			
5	Nameplate design drawing		09			
6	Packing information		10			
7	Test report Including: Electrical test report California Energy Commission Test Repot Certification approve sheet					
		tatus				
8	UL/cUL Certificate.	ок	13-14			
			ROHS			
		k	1			

	CUCTOM	-D	I I	SIONS	
	CUSTOME JSTOMER			DESIGNED NO.	ST241A
REV.	REVISER			MODEL NO.	
A	KEVIOLIK	090206	To creating new drawing SPEC	DESCRIPTION	
		000200	is distantly new diaming of Eo		
			-		
		- 1			·au
10					/,0
					Roll
					(00)
- 1					1

ELECTRICAL REQUIREMENTS

DESIGNED NO. ST241A DATE 090206 REVISION A

ADAPTER

1. Electrical:

1-1. Input Characteristics:

1-1-1.Rated Voltage

It is normal for 100 Vac to 240 Vac input AC voltage

1-1-2.Input Voltage Range

The Adapter shall operate form 90 Vac to 264 Vac input AC voltage

1-1-3.Rated Frequency

It is normal for <u>50</u> Hz to <u>60</u> Hz and single phase.

1-1-4.Frequency Range

The Adapter shall operate with an input frequency form 47 Hz to 63 Hz.

1-1-5.Steady AC Current

Maximum steady state input current is less than 0.8 Arms. Measured at 100Vac Input voltage.

1-1-6.Inrush Current

AT FULL LOAD ,25 DEGREE C, COLD START

115V	AC,60Hz INPUT	NO damage shall be occurred and the input
230V	AC,50Hz INPUT	fuse shall not be blown up

1-1-7. Minimum Average Efficiency In Active

78.6 % min. measured at I/P:115Vac/60Hz& Active Loading:25%/50%/75%/100%

 $[0.09x Ln_{(24V x1A)} + 0.5] * 100\% = 78.6\%$ (Criteria : Level IV)

1-1-8.No load power (Stand-by consumption)

The no load power is less than <u>0.5</u> W at <u>115</u> Vac and <u>230</u> Vac (Criteria: Level IV)

1-2. Output Characteristics:

1-2-1.Rated Voltage

The rated output voltage is specified at 24 Vdc.

1-2-2. Voltage Range

The output voltage will be performed from 24 Vdc±5%.

1-2-3.Line Regulation

The output voltage is specified at Vout ± 2 %.

1-2-4.Load Regulation

The output voltage is specified at Vout ± 5 %.

1-2-5.Current

This Adapter can work form _0_ A to _1_A(full load) and output voltage is in section 2 specified range.



	Frepared by	Reviewed by	Approved by
ELECTRONICS			

ELECTRICAL REQUIREMENTS

DESIGNED NO. ST241A DATE 090206 REVISION A

1-2-6.Rated Power

This Adapter capable to support 24 Watts continuously at all specified conditions.

1-2-7.Output Ripple and Noise

Ripple & noise ≤ 240 mVp-p

Measured methods:

Performed by 20MHz bandwidth in oscilloscope. Applied 0.1uF ceramic capacitor and 10uF electrolytic capacitor across output connector terminal. Measured at the end of DC cable.

1-2-8.Turn On Delay Time (Power On Time)

- 3 S maximum. Tested @ 100 Vac and 240 Vac input and 24 W full load at output 1-2-9. Hold Up Time
 - 8 mS Min at Max Load 100 Vac/60Hz (O/P Typic Voltage Drop Down 10%)
 - 8 mS Min at Max Load 240 Vac/50Hz (O/P Typic Voltage Drop Down 10%)

1-2-10.Protection

a) Short Circuit protection

The Adapter is protected that a short happened between the output terminals and shall not result in a fire hazard, and will be normal operation automatically while the short is removed.

b) Over current protection

No safety hazard

c) Over voltage protection

No safety hazard

2. Environmental:

2-1.Temperature

2-1-1.Operating

The Adapter is capable to operate form 0 °C to 40°C.

2-1-2.Non-Operating

The Adapter is capable to be stored form -10°C to 60°C.

2-2.Humidity

2-2-1.Operating

The Adapter is capable to operate form 10to 90% RH. (non condensing)

2-2-2.Non-Operating


The Adapter is capable to be stored form 5 to 95% RH. (non condensing)




	Prepared by	Reviewed by	Approved by
ELECTRONICS	₩-		

ESIGNED N	O. ST241A	DAT	TE	090206	REVISION		Α
2-3.Dielel	tric Withstand Voltage (H	I – POT)					
	dapter shall be applied 3					etween AC	input
2-4.Insula	tion Resistance						
Primar	ry to secondary: > 10	_M ohm.	500 VDC		6		
2-5.EMI R	Requirement						
The ad	lapter complies with:	FCC Part 1	15 Class B	□EN5502	22 Class B □VCCI	Class B	
		AS/NES 35	548 Class B	□CNS13	438 Class B □ICES	-003 Class	s B
		GB9254 C	lass B	□Other_			
2-6.EMS							
(2	Common Mode Differential Mode Conforming		10.5	17.10	earm, neutral to earm,	ine to net	itrai)
Type	Standard	Meet	Approved	Туре	Standard	Meet	Approve
☑UL	UL60950-1			□СВ	IEC60950-1		
☑cUL	CSA 22.2 No.60950			□SAA	AS/NZS: 60950-1		
□ TUV-GS	EN60950-1			□ccc	GB4943	0	
□PSE	J60950-1		0	□CE	EN60950-1 EN60065		
Charles as	CNS 13436,CNS13438			□KETI	K 60950-1		
□BSMI			2000	Поп		-	
☐ TUV-GS 3. Mechan				□СВ			,
3. Mechan 3-1.Dimen Body 3-2.Outpu Plug: 3-3.Weigh	ical: sion : 97 mm (L) × 55 mm (W) t Cord See page 9 t Veight (Approx): 117 g.		nacres es	beconstor		dis	,

PCB VIEW ST241A DESIGNED NO. DATE 090206 REVISION Α TOP LAYOUT **BOTTOM LAYOUT BOTTOM LAYOUT** Prepared by Approved by Reviewed by **ELECTRONICS**





, INN	ER BOX	LENGTH	98mm +/- 1.0mm					
ϵ	$\overline{}$	WIDTH	56mm +/	- 1.0mm				
<u>/</u>		HIGHNESS	Transport to the control of the cont					
TY-	/-	MATERIAL	450g MIN.					
н	1,	COLOR	White	and the second				
4		PRINTING	N/A					
	—	BOX NO.						
MASTE	R CARTON							
200		LENGTH	35.1cm					
H		WIDTH	31cm	31cm				
		HIGHNESS	32.5cm	32.5cm				
		MATERIAL	5 layers wave cardboard					
w 🔾		PCS/CTN	90 pcs					
•								
SHIPING	G MARKING							
		Main marking		Side marking(Green))	
		- 37						
ESIGNED NO.		ST241A						
RAWING NO.		ST241A						
COLOR								
COLOR MATERIAL		Creating new drawing SPEC.		090206	A	100	DEVICE	
COLOR		Creating new drawing SPEC. DESCRIPTION	Prepared by	090206 DATE Reviewed	RE	V.	REVISER proved by	

DECIGNED NO			-	_	***) TI NO	,	- 6	OT	2444	
DESIGNED NO.				+		DEL NO				241A	
CUSTOMER P/N					L	DATE		_	09	0206	
ITEM	SPEC.	1	2	3	4	5 N). 6	7	8	9	10
INPUT 100VAC 60Hz						1					
Stand by power	0.5W Max	0.28	0.26	0.26	0.27	0.27					
Input current (rms) Load 1000 mA	800mA Max.	485.5	494.8	494.5	494.8	491.4					
Output voltage Load <u>0</u> mA	24VDC +/- 5%	23.99	24.06	24.02	23.99	24.07					
Output voltage Load <u>1000</u> mA	24VDC +/- 5%	23.94	24.01	23.97	23.94	24.02					
Efficiency Load <u>1000</u> mA	78.6% Min	85.93	85.99	85.73	85.87	86.21					
Output Ripple and Noise Load <u>1000</u> mA	240 mV Max	96	99	106	10	96					
Short Test		ок	ок	ок	ок	ок					
INPUT 240VAC 50Hz											
Stand by power	0.5W Max	0.38	0.37	0.38	0.38	0.37					
Input current (rms) Load 1000 mA	800mA Max.	288.1	290.1	262.6	293.4	295.5					
Output voltage Load <u>0</u> mA	24VDC +/- 5%	23.99	24.06	24.2	23.99	24.07					÷
Output voltage Load <u>1000</u> mA	24VDC +/- 5%	23.94	24.01	23.97	23.94	24.02					
Efficiency Load <u>1000</u> mA	78.6% Min	86.48	86.21	86.44	86.61	86.39					
Output Ripple and Noise Load 1000 mA	240 mV Max	63	65	61	62	63					
Short comeback		ок	ок	ок	ок	ок					1
HI-POT P - S: DC 424 TEST 60 Sec	12V 10mA	PASS	PASS	PASS	PASS	PASS			/	die	2/
								<	3	0	
						Prepare	d by	Reviewe	d by	Approv	ved by
ELECTRONICS				₩	—						460

CUSTOMER P/N ITEM					MODE	L NO.			ST2	41A	
ITEM					DAT	ΓE			090	206	
	SPEC.					N	0.				
	OF LO.	1	2	3	4	5	6	7	8	9	10
INPUT 115VAC 60Hz)					
Stand by power	0.5W Max	0.28	0.27	0.26	0.28	0.26					
Efficiency Load 25% <u>250</u> mA	_	81.35	81.91	81.44	81.34	81.72					
Efficiency Load 50% <u>500</u> mA		83.51	83.84	83.33	83.34	83.97					
Efficiency Load 75% <u>750</u> mA		84.17	84.37	84.07	84.12	84.53					
Efficiency Load 100% 1000 mA	-	86.36	86.42	86.22	86.30	86.52					
AVERAGE EFFICIENCY	78.6% Min	83.84	84.16	83.76	83.77	84.18					
INPUT 230VAC 50Hz											
Stand by power	0.5W Max	0.35	0.35	0.36	0.36	0.36					
Efficiency Load 25% _250 mA		79.59	80.38	80.03	79:19	80.05					
Efficiency Load 50% _500 mA		82.99	84.37	83.88	83.11	83.68					
Efficiency Load 75% _750_ mA		84.56	85.01	84.79	84.44	84.85					4
Efficiency Load 100% <u>1000</u> mA		86.73	86.96	86.65	86.64	87.02					
AVERAGE EFFICIENCY	78.6% Min	83.46	84.18	83.83	83.34	83.90					